

Tapit ezBox Configuration Guide

TAPIT EZBOX CONFIGURATION GUIDE FOR Panasonic via IP

1. Open Trisys IP Collector and click Stop Service if it is available.
2. Click Create a New Site/Location
3. Enter a Site Location Name. Enter the PBX IP Address under Remote Phone system IP and enter the SMDR Port in the Port field.
4. Check the box labeled Send Login Information
5. Under Login String enter "smdr{CR}1234{CR}" without quotes where 1234 is the SMDR password set in the Panasonic.
6. Click Save
7. Click Start Service
8. Status should change to Received New Data. This will indicate it is collecting data.

Trisys Inc.
187 Columbia Turnpike
Suite 484
Florham Park, NJ 07932

www.trisys.com

Phone: 973-360-2300
Fax: 973-360-2222
Email: general@trisys.com